

www.padauk.com.tw

 產品專區
Products

OTP – SOVA (经济适用型)

Please don't apply to high EFT requirement application * : under development

Series	FPPA	ADC (max)	IO (max)	ROM (word)	RAM (byte)	LCD (% VDD)	PWM	Special Functions	Package	Re
PMS150C	1	--	6	1KW	64	--	--	--	SOT23-6, SOP8 DIP8, MSOP10	PMS150B, 513 2501C, 12C509
PMS154B	1	--	14	2KW	128	4	8bit x 2 11bit x 1	CMP x 1	SOT23-6, SOP8, MSOP10 SOP14, SOP16	PMS154
New PMS132	1	12bit x 12ch	14	2KW	128	--	8bit x 2 11bit x 1	8x8 Multiplier CMP x 1	SOP8, SOP14, SOP16 QFN3x3-16L	PMS131, PMS130, 2711+, 71AS+
* PMS134	1	12bit x 12ch	22	4KW	256	4	8bit x 2 11bit x 1	8x8 Multiplier CMP x 1	SOP16, SOP20, SOP24 SSOP24, QFN4x4-24L	PMS132+

OTP – Commercial Grade (商規)

Please don't apply to high EFT requirement application * : under development

Series	FPPA	ADC (max)	IO (max)	ROM (word)	RAM (byte)	LCD (% VDD)	PWM	Special Functions	Package	Re
PMS150	1	--	7	1KW	60	--	--	--	SOT23-6, SOP8 DIP8, MSOP10	513 2501C, 12C509
PMS153	1	--	12	1KW	60	--	--	--	SOP14, DIP14	153, 2511, 16C505
PMS156	1	--	16	1KW	60	4	--	--	SOP16, SOP18, SOP20 DIP16, DIP18, DIP20	156, 16C56
PMS271	2	8bit x 8ch	16	1KW	64	4	--	--	SOP16, SOP18, SOP20 DIP16, DIP18, DIP20	16C71
PMS130/131	1	12bit x 12ch	14	1.5KW	88	--	8bit x 2	8bit x 8bit Multiplier (1T)	SOP8, SOP14, SOP16 DIP14, DIP16	2711+, 71AS+
PMS232	2	12bit x 10ch	18	2KW	160	4	8bit x 1	--	SOP14, SOP16, SOP20	78P259, 2712+
PMS234	2	12bit x 11ch	26	4KW	208	4	8bit x 1	CMP x 1	SOP20, SOP24, SOP28	78P346, 2712+

OTP – Industrial Grade (High EFT, 工規)

* : under development

Series	FPPA	ADC (max)	IO (max)	ROM (word)	RAM (byte)	LCD (% VDD)	PWM	Special Functions	Package	Re
PMC150	1	--	7	1KW	60	--	--	--	SOT23-6, SOP8 DIP8, MSOP10	131, 513 2501C, 12C509
PMC153	1	--	12	1KW	60	--	--	--	SOP14, DIP14	153, 2511, 16C505
PMC156	1	--	16	1KW	60	4	--	--	SOP16, SOP18, SOP20 DIP16, DIP18, DIP20	156, 16C56
PMC251	2	--	12	1KW	60	--	--	--	SOP8, SOP14 DIP8, DIP14	153+, 2511+
PMC271	2	8bit x 8ch	16	1KW	64	4	--	--	SOP16, SOP18, SOP20 DIP16, DIP18, DIP20	16C71
PMC131	1	12bit x 12ch	14	1.5KW	88	--	8bit x 2	8bit x 8bit Multiplier (1T)	SOT23-6, SOP8, SOP14 SOP16, DIP8, DIP14, DIP16	2711+, 71AS+
PMC232	2	12bit x 10ch	18	2KW	160	4	8bit x 1	--	SOP14, SOP16, SOP20 DIP14, DIP16, DIP20	78P259, 2712+
PMC234	2	12bit x 11ch	26	4KW	208	4	8bit x 1	CMP x 1	SOP20, SOP24, SOP28 DIP20, SKDIP24, SKDIP28	78P346, 2712+